



WANSEMI
万芯半导体

WX017P02S3

Enhancement Mode P-Channel Power MOSFET

SOT23-3/PMOS/-20V/ ± 12 V/-0.7V/-5A/18m Ω

Rev1.0


-20V, 18mΩ, -5A, P-Channel MOSFET

1.Features

- ◆ Advanced Trench Technology
- ◆ Surface mount package


2.Applications

- ◆ Power Management
- ◆ Load Switching



SOT23-3

Pin Description



Schematic Diagram

| V_{DS} | $R_{DS(on)}$ Typ. | I_D |
|----------|-------------------|-------|
| -20V | 18mΩ @ -4.5V | -5A |
| | 21.8mΩ @ -2.5V | |

3.Package Marking and Ordering Information

| Part no. | Marking | Package | PCS/Reel | PCS/CTN. |
|------------|---------|---------|----------|----------|
| WX017P02S3 | 017P02 | SOT23-3 | 3,000 | 180,000 |

4.Absolute Max Ratings at Ta=25°C (Note1)

| Parameter | Symbol | Maximum | Units |
|---|-----------|-------------|-------|
| Drain to Source Voltage | V_{DSS} | -20 | V |
| Gate to Source Voltage | V_{GSS} | ±12 | V |
| Drain Current (DC) | I_D | -5 | A |
| Drain Current (Pulse), $PW \leq 300\mu s$ | I_{DP} | -20 | A |
| Total Dissipation | P_D | 1.1 | W |
| Junction Temperature | T_j | 150 | °C |
| Storage Temperature | T_{stg} | -55 to +150 | °C |

Note 1: Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected.

5.Thermal Resistance Ratings (Note 2)

| Parameter | Symbol | Value | Unit |
|---------------------|-----------------|-------|------|
| Junction to Ambient | $R_{\theta JA}$ | 114 | °C/W |


Note 2: When mounted on 1 inch square copper board $t \leq 10\text{sec}$ The value in any given application depends on the user's specific board design.

6. Electrical Characteristics at Ta=25°C (Note 3)


| Parameter | Symbol | Test Conditions | Min. | Typ. | Max. | Units |
|--|---------------|---|------|------|-----------|------------|
| Drain to Source Breakdown Voltage | $V_{(BR)DSS}$ | $I_D = -250\mu A, V_{GS} = 0V$ | -20 | - | - | V |
| Zero-Gate Voltage Drain Current | I_{DSS} | $V_{DS} = -20V, V_{GS} = 0V$ | - | - | -1 | μA |
| Gate to Source Leakage Current | I_{GSS} | $V_{GS} = \pm 12V, V_{DS} = 0V$ | - | - | ± 100 | nA |
| Gate Threshold Voltage | $V_{GS(th)}$ | $V_{DS}=V_{GS}, I_{DS}=-250\mu A$ | -1.0 | -1.5 | -2.5 | V |
| Static Drain to Source On-State Resistance | $R_{DS(on)}$ | $I_D = -5A, V_{GS} = -4.5V$ | - | 18 | 23 | m Ω |
| | | $I_D = -4A, V_{GS} = -2.5V$ | - | 21.8 | 30 | m Ω |
| Input Capacitance | C_{iss} | $V_{GS}=0V,$ $V_{DS}=-10V,$ Frequency=1.0MHz | - | 1200 | - | pF |
| Output Capacitance | C_{oss} | | - | 191 | - | pF |
| Reverse Transfer Capacitance | C_{rss} | | - | 168 | - | pF |
| Turn-ON Delay Time | $t_{d(on)}$ | $V_{DD} = -10V, I_D = -5A,$ $R_G = 10\Omega, V_{GS} = -4.5V$ | - | 11 | - | ns |
| Rise Time | t_r | | - | 35 | - | ns |
| Turn-OFF Delay Time | $t_{d(off)}$ | | - | 30 | - | ns |
| Fall Time | t_f | | - | 10 | - | ns |
| Total Gate Charge | Q_g | $V_{DS} = -10V,$ $V_{GS} = -4.5V,$ $I_D = -5A$ | - | 33.7 | - | nC |
| | Q_{gs} | | - | 3.5 | - | nC |
| | Q_{gd} | | - | 10.5 | - | nC |
| Diode Forward Voltage | V_{FSD} | $I_{SD} = -5A, V_{GS} = 0$ | -0.5 | - | -1.2 | V |

Note 3: Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.


7. Typical Electrical and Thermal Characteristics




Typical Output Characteristics




Typical Transfer Characteristics




On-resistance vs. Drain Current




Body Diode Characteristics




Gate Charge Characteristics




Capacitance Characteristics




Normalized Breakdown voltage vs. Junction Temperature




Normalized on Resistance vs. Junction Temperature



Normalized Breakdown voltage vs. Junction Temperature




Current De-rating



Normalized Maximum Transient Thermal Impedance

8.Package Dimensions



DIMENSIONS (unit : mm)

| Symbol | Min | Typ | Max | Symbol | Min | Typ | Max |
|----------------------|------|------|------|----------------------|------|------|------|
| A | 1.00 | 1.17 | 1.30 | A₁ | 0.01 | 0.05 | 0.10 |
| b_p | 0.35 | 0.39 | 0.50 | c | 0.10 | 0.20 | 0.26 |
| D | 2.70 | 2.90 | 3.10 | E | 1.30 | 1.58 | 1.70 |
| e | -- | 1.90 | -- | e₁ | -- | 0.95 | -- |
| H_E | 2.50 | 2.78 | 3.00 | L_p | 0.20 | 0.32 | 0.60 |
| Q | 0.23 | 0.27 | 0.33 | v | -- | 0.20 | -- |
| w | -- | 0.20 | -- | | | | |

9.Important Notice

WAN SEMICONDUCTOR (NINGBO) CO.,LTD reserves the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services and to discontinue any product or service. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products (also referred to herein as “components”) are sold subject to WANSEMI’s terms and conditions of sale supplied at the time of order acknowledgment.

WANSEMI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in WANSEMI’s terms and conditions of sale of semiconductor products. Testing and other quality control techniques are used to the extent WANSEMI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

WANSEMI assumes no liability for applications assistance or the design of Buyers’ products. Buyers are responsible for their products and applications using WANSEMI components. To minimize the risks associated with Buyers’ products and applications, Buyers should provide adequate design and operating safeguards.

No WANSEMI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed a special agreement specifically governing such use.

Unless WANSEMI has specifically designated certain components which meet ISO/TS16949 requirements, mainly for automotive use, WANSEMI will not be responsible for any failure of such components to meet such requirements.